



# MODEL: 91733ORB

## PACKING DIAGRAM





## MODEL: 91733ORB ASSEMBLY INSTRUCTIONS-1 READ AND SAVE THESE INSTRUCTIONS

READ INSTRUCTIONS ALL THE WAY THROUGH PRIOR TO ASSEMBLY.

THIS FIXTURE SHOULD TAKE APPROXIMATELY 15 MINUTES TO ASSEMBLE.

MAKE SURE ALL PARTS ARE FIRMLY TIGHTENED.

**TOOLS:** YOU WILL NEED THE FOLLOWING TOOLS OR EQUIPMENT: LADDER, SCREWDRIVER, ADJUSTABLE WRENCH, WIRE CUTTERS AND PLIERS.

### UNPACK THE FIXTURE

YOU SHOULD HAVE RECEIVED THE FOLLOWING PARTS IN THE PACKAGE: CANOPY, CHAIN, CHAIN LOOP, POLE ASSEMBLY, SHADE, STEM, FIXTURE BODY, (3) CANDLE SLEEVES AND (7) GLASS DROPS. TO PROTECT THE FINISH, PLACE ALL PARTS ON A SOFT SURFACE.


### MOUNTING HARDWARE PACKAGE:

SCREW COLLAR LOOP, SCREW COLLAR NUT, NUT, NIPPLE, (4) 8-32 X 1-1/4" SCREWS, CROSSBAR, GREEN GROUND SCREW, MOUNTING PLATE AND (3) WIRE CONNECTORS.

NOTE: IF MOUNTING AS PENDANT, PROCEED TO INSTRUCTION BELOW. IF MOUNTING AS FLUSH MOUNT PROCEED TO ASSEMBLY INSTRUCTION-2.

### FIXTURE ASSEMBLY

1. SCREW STEM TO TOP OF DISTRIBUTOR.
2. SLIDE NIPPLE OF STEM INTO NOTCH OF RING, THEN SCREW POLE ASSEMBLY TO END OF THE NIPPLE.
3. SCREW CHAIN LOOP TO TOP OF POLE ASSEMBLY.
4. DETERMINE THE LENGTH OF CHAIN REQUIRED TO HANG THE FIXTURE AT THE DESIRED HEIGHT. USING PLIERS, OPEN ONE END LINK OF CHAIN AND ATTACH TO THE CHAIN LOOP ON TOP OF THE FIXTURE. REMOVE OR ADD CHAIN AS DESIRED AT THIS TIME. LACE FIXTURE WIRE AND GROUND WIRE UP THROUGH EVERY OTHER LINK OF CHAIN.




### TO OPEN A CHAIN LINK

USE A PAIR OF PLIERS AND A SCREWDRIVER AS SHOWN ABOVE TO OPEN A CHAIN LINK. WRAP THE JAWS OF THE PLIERS WITH CLOTH TO PROTECT THE FINISH OF THE CHAIN.

**\*\*STOP\*\* COMPLETE INSTALLATION INSTRUCTIONS-1 ON NEXT PAGE BEFORE CONTINUING TO FINAL ASSEMBLY.**

### FINAL ASSEMBLY

1. SLIDE A CANDLE SLEEVE OVER EACH SOCKET.
2. INSTALL A 60 WATT MAXIMUM CANDELABRA BASE TYPE "B" BULB (NOT INCLUDED) INTO EACH SOCKET.
3. ATTACHE (7) GLASS DROPS TO THE RINGS ON ARMS AND THE RING ON BOTTOM OF DISTRIBUTOR AS SHOWN.
4. RESTORE POWER, YOUR NEW FIXTURE IS NOW READY FOR USE.



## **INSTALLATION INSTRUCTIONS-1** **READ AND SAVE THESE INSTRUCTIONS**

### **CAUTION**

TO AVOID POSSIBLE ELECTRIC SHOCK, MAKE SURE THE ELECTRICITY IS SHUT OFF AT THE MAIN PANEL. IF YOU ARE REPLACING AN EXISTING FIXTURE, FIRSTLY, TURN THE FIXTURE OFF. NEXT, TURN THE WALL SWITCH OFF. FINALLY, GO TO THE MAIN FUSE OR BREAKER BOX IN YOUR HOME. TURN THE FUSE OR BREAKER TO THE OFF POSITION. SOME TYPES OF FUSES MUST BE UNSCREWED TO SHUT OFF THE POWER.

\* ALL WIRING MUST BE DONE IN ACCORDANCE WITH NATIONAL AND LOCAL ELECTRIC CODES. IF YOU ARE NOT FAMILIAR WITH WIRING, YOU SHOULD USE A QUALIFIED ELECTRICIAN.

\*\* THIS FIXTURE IS INTENDED TO BE MOUNTED TO A UL LISTED OUTLET BOX CAPABLE OF SUPPORTING THE FIXTURE.

### **COMPLETE FIXTURE ASSEMBLY INSTRUCTIONS-1 FIRST (SEE PREVIOUS PAGE).**

1. ATTACH THE CROSSBAR TO THE CEILING OUTLET BOX USING THE TWO SCREWS PROVIDED WITH THE OUTLET BOX. (NOTE: IF THE SCREWS WITH THE OUTLET BOX ARE TOO SHORT, USE THE (2) 8-32 x 1-1/4" SCREWS PROVIDED IN THE MOUNTING HARDWARE PACKAGE). NEXT, SCREW THE SCREW COLLAR LOOP ONTO THE NIPPLE AND THEN SCREW THE NIPPLE INTO THE CROSSBAR.


2. SLIDE THE SCREW COLLAR NUT AND THEN THE CANOPY THAT HAS ONE HOLE ONTO THE END OF THE CHAIN. THEN FASTEN THE END LINK OF CHAIN TO THE SCREW COLLAR LOOP.

3. INSERT THE FIXTURE WIRE AND THE GROUND WIRE UP THROUGH THE NIPPLE. CONNECT THE WHITE OR RIBBED FIXTURE WIRE TO THE WHITE SUPPLY WIRE IN THE OUTLET BOX USING THE TWIST-ON WIRE CONNECTORS PROVIDED. CONNECT THE BLACK OR SMOOTH FIXTURE WIRE TO THE BLACK SUPPLY WIRE IN THE SAME MANNER. INSTALL THE FIXTURE GROUND WIRE UNDER THE GREEN GROUND SCREW ON THE CROSSBAR THEN CONNECT THE FIXTURE GROUND WIRE TO THE SUPPLY GROUND WIRE IN THE OUTLET BOX USING THE TWIST-ON WIRE CONNECTOR PROVIDED.

4. TUCK THE WIRES CAREFULLY INSIDE THE OUTLET BOX. SPREAD THE ELECTRICAL SPLICES SO THAT THE BLACK WIRES ARE ON ONE SIDE OF THE OUTLET BOX AND THE WHITE WIRES ARE ON THE OTHER SIDE. NEXT RAISE THE CANOPY TO THE CEILING AND SECURE IN PLACE BY SCREWING THE SCREW COLLAR NUT ONTO THE SCREW COLLAR LOOP.

5. SEE PREVIOUS PAGE FOR FINAL ASSEMBLY INSTRUCTIONS.





## MODEL: 91733ORB ASSEMBLY INSTRUCTIONS-2 READ AND SAVE THESE INSTRUCTIONS

READ INSTRUCTIONS ALL THE WAY THROUGH PRIOR TO ASSEMBLY.

THIS FIXTURE SHOULD TAKE APPROXIMATELY 15 MINUTES TO ASSEMBLE.

MAKE SURE ALL PARTS ARE FIRMLY TIGHTENED.

TOOLS: YOU WILL NEED THE FOLLOWING TOOLS OR EQUIPMENT: LADDER, SCREWDRIVER, ADJUSTABLE WRENCH, WIRE CUTTERS AND PLIERS.

### UNPACK THE FIXTURE

YOU SHOULD HAVE RECEIVED THE FOLLOWING PARTS IN THE PACKAGE: CANOPY, CHAIN, CHAIN LOOP, POLE ASSEMBLY, SHADE, STEM, FIXTURE BODY, (3) CANDLE SLEEVES AND (7) GLASS DROPS. TO PROTECT THE FINISH, PLACE ALL PARTS ON A SOFT SURFACE.

### MOUNTING HARDWARE PACKAGE:

SCREW COLLAR LOOP, SCREW COLLAR NUT, NUT, NIPPLE, (4) 8-32 X 1-1/4" SCREWS, CROSSBAR, GREEN GROUND SCREW, MOUNTING PLATE AND (3) WIRE CONNECTORS.

NOTE: IF MOUNTING AS FLUSH MOUNT, PROCEED TO INSTRUCTION BELOW. IF MOUNTING AS PENDANT PROCEED TO ASSEMBLY INSTRUCTION-1.

### FIXTURE ASSEMBLY


1. REMOVE (2) BALL FINIALS FROM CANOPY BY UNSCREWING (2) SMALL SCREWS IN CANOPY.
2. SCREW STEM TO TOP OF DISTRIBUTOR.
3. SLIDE NIPPLE OF STEM INTO NOTCH OF RING, THEN SCREW POLE ASSEMBLY TO END OF THE NIPPLE.
4. CUT THE FIXTURE SUPPLY WIRE, LEAVING AT LEAST 15.2 CM (6") LENGTH ABOVE CANOPY FOR ELECTRICAL CONNECTING.


**\*\*STOP\*\* COMPLETE INSTALLATION INSTRUCTIONS-2 ON NEXT PAGE BEFORE PROCEEDING.**

### FINAL ASSEMBLY

1. SLIDE A CANDLE SLEEVE OVER EACH SOCKET.
2. INSTALL A 60 WATT MAXIMUM CANDELABRA BASE TYPE "B" BULB (NOT INCLUDED) INTO EACH SOCKET.
3. ATTACHE (7) GLASS DROPS TO THE RINGS ON ARMS AND THE RING ON BOTTOM OF DISTRIBUTOR AS SHOWN.
4. RESTORE POWER, YOUR NEW FIXTURE IS NOW READY FOR USE.

AVAILABLE PARTS ARE:  
91733SHORB (SHADE)  
91730CRYS (GLASS DROP)





## INSTALLATION INSTRUCTIONS-2

### READ AND SAVE THESE INSTRUCTIONS

**CAUTION:** TO AVOID POSSIBLE ELECTRIC SHOCK, MAKE SURE THE ELECTRICITY IS SHUT OFF AT THE MAIN PANEL. IF YOU ARE REPLACING AN EXISTING FIXTURE, FIRSTLY, TURN THE FIXTURE OFF. NEXT, TURN THE WALL SWITCH OFF. FINALLY, GO TO THE MAIN FUSE OR BREAKER BOX IN YOUR HOME. TURN THE FUSE OR BREAKER TO THE OFF POSITION. SOME TYPES OF FUSES MUST BE UNSCREWED TO SHUT OFF THE POWER.

\* ALL WIRING MUST BE DONE IN ACCORDANCE WITH NATIONAL AND LOCAL ELECTRIC CODES.

\*\* IF YOU ARE NOT FAMILIAR WITH WIRING, YOU SHOULD USE A QUALIFIED ELECTRICIAN.

\*\*\* THIS FIXTURE IS INTENDED TO BE MOUNTED TO A UL LISTED OUTLET BOX CAPABLE OF SUPPORTING THE FIXTURE.

### COMPLETE FIXTURE ASSEMBLY INSTRUCTIONS-2 FIRST (SEE PREVIOUS PAGE).

1. SCREW (2) 8-32 x 1-1/4" SCREWS INTO THE CROSSBAR MAKING SURE THAT THEY LINE UP WITH THE HOLES IN THE CANOPY. ATTACH THE CROSSBAR TO THE CEILING OUTLET BOX USING THE TWO SCREWS PROVIDED WITH THE OUTLET BOX. (NOTE: IF THE SCREWS WITH THE OUTLET BOX ARE TOO SHORT, USE THE (2) 8-32 x 1-1/4" SCREWS PROVIDED IN THE MOUNTING HARDWARE PACKAGE).
2. CONNECT THE WHITE OR RIBBED FIXTURE WIRE TO THE WHITE SUPPLY WIRE IN THE OUTLET BOX USING THE TWIST-ON WIRE CONNECTORS PROVIDED. CONNECT THE BLACK OR SMOOTH FIXTURE WIRE TO THE BLACK SUPPLY WIRE IN THE SAME MANNER. INSTALL THE FIXTURE GROUND WIRE UNDER THE GREEN GROUND SCREW ON THE CROSSBAR THEN CONNECT THE FIXTURE GROUND WIRE TO THE SUPPLY GROUND WIRE IN THE OUTLET BOX USING THE TWIST-ON WIRE CONNECTOR PROVIDED.
3. TUCK THE WIRES CAREFULLY INSIDE THE OUTLET BOX. SPREAD THE ELECTRICAL SPLICES SO THAT THE BLACK WIRES ARE ON ONE SIDE OF THE OUTLET BOX AND THE WHITE WIRES ARE ON THE OTHER SIDE.
4. RAISE THE FIXTURE ASSEMBLY TO THE CEILING AND SECURE IN PLACE WITH (2) BALL FINIALS.
5. SEE ASSEMBLY INSTRUCTIONS-2 FOR FINAL ASSEMBLY INSTRUCTIONS.

